


Connection cables and safety screws

Flying lead
M8 snap-on, 6-pin

Dimension drawing


View of connection side



- 1 = BN ▶ U_B
- 2 = WH ▶ OA
- 3 = BU ▶ 0 V
- 4 = BK ▶ OB
- 5 = GY ▶ OUT
- 6 = PK ▶ NC

Flying lead
M12 female plug 5-pin


View of connection side



- 1 = BN ▶ U_B
- 2 = WH ▶ OA
- 3 = BU ▶ 0 V
- 4 = BK ▶ OB
- 5 = GY ▶ OUT

Flying lead
M12 female plug 8-pin

View of connection side



- 1 = WH ▶ IB
- 2 = BN ▶ UB
- 3 = GN ▶ OA
- 4 = YE ▶ OB
- 5 = GY ▶ OUT
- 6 = PK ▶ IA
- 7 = BU ▶ 0 V
- 8 = RD ▶ RST

Ordering table

Series	Comment	Order no. / item
Connection cable M8 snap-on PVC 6-core, flying lead for the connection of one CES-AP-C.2...SF	M8 snap-on 6-pin, length 5 m	103 556 C-R08F06-06X014PV05,0-ES-103556
	M8 snap-on 6-pin, length 10 m	103 557 C-R08F06-06X014PV10,0-ES-103557
	M8 snap-on 6-pin, length 15 m	103 558 C-R08F06-06X014PV15,0-ES-103558
	M8 snap-on 6-pin, length 20 m	103 559 C-R08F06-06X014PV20,0-ES-103559
	M8 snap-on 6-pin, length 25 m	103 560 C-R08F06-06X014PV25,0-ES-103560
Connection cable M12 PVC 5-core, flying lead for the connection of one CES-AP-C.1...SB / CES-AP-C.2...SB	M12-Buchsenstecker 5-polig, Länge 5 m	100 183 C-M12F05-05X034PV05,0-ZN-100183
	M12-Buchsenstecker 5-polig, Länge 10 m	100 184 C-M12F05-05X034PV10,0-ZN-100184
	M12-Buchsenstecker 5-polig, Länge 20 m	100 185 C-M12F05-05X034PV20,0-ZN-100185
Connection cable M12 PVC 8-core, flying lead for the connection of one CES-AP-C01...SA	M12 female plug 8-pin, length 5 m	100 177 C-M12F08-08X025PV05,0-ZN-100177
	M12 female plug 8-pin, length 10 m	100 178 C-M12F08-08X025PV10,0-ZN-100178
	M12 female plug 8-pin, length 20 m	100 179 C-M12F08-08X025PV20,0-ZN-100179
Safety screws (replacement) for safety switch CES-AP-C.2... and actuator CES-A-BLN...	M4 x 14 Packaging unit 100 pcs.	074 063 Safety screws M4 x 14